MIRЯORSTONE

Slimline Driver 150W



Product Description

The Slimline Driver 150w is a part of our thinnest and most efficient range yet. Sized at 322.6mm x 30.1mm x 21.5mm, it is streamline and small enough to be easily concealed in any area and still convert the same amount of energy as other power supplies.

Product Features

- Constant voltage/ PWM Output
- Leading edge dimmable
- AC input: 180-240VAC
- Efficiency up to 86%
- Protections: Short circuit/ Over loading/ Over current/ Over temperature
- Full protection aluminium housing easy installation
- Cooling by free air convection
- Suitable for LED lighting and moving signs
- 3 year warranty










Technical Dimensions



MIRЯORSTONE

Slimline Driver 150W

Technical Specifications

Output Specifications		
Output Voltage	12V	24V
Voltage Tolerance	150mV	
Output Current	12.5A	6.25A
Rated Power	150W	
Input Specifications		
Input Voltage	200-240VAC	
Frequency Range	50-60Hz	
Inrush Current	<60A	
Full Load Efficiency (Typ.)	90%	
AC Current (Max.)	1A	
Power Factor	PF >0.9/240VAC (Full Loading)	
Protection		
Short Circuit	Shut down o/p voltage, re-power onto recover after fault condition is removed	
Over Loading	<120%, Shut down o/p voltage, re-power onto recover	
Over Temperature	115°C shut down o/p voltage, re-power on to recover	
Protection Class	II	
Environment		
Working Temperature	-20~+45°C (Refer to derating curve), +80°C (max case temp.)	
Working Humidity	45-85%	
Safety & EMC		
Safety standards	EN613471, EN61347-2-13	
EMS	EN61000-3-2; EN61000-3-3; EN61547	
EMF	EN62493-2010	
ERP	EN1194-2012	
Other Specifications		
IP Rating	IP20	
Weight	0.29 Kg	
Size	322.6 x 30.1 x 21.5 mm	