

### Varilight 3 Gang 2 Way LED Dimmer Switch (V-Pro & V-Com)



#### Product Description

This superb 3-gang rotary dimmer switch is to be had in both the V-Pro and the V-Com versions, which will allow you to control up to 10 and up to 25 bulbs respectively. Your application will dictate the choice you make.

Possibly the most straightforward of all Varilight's models, this features a simple Push On/Off switch, with rotary dimming functionality.

#### Product Features

**Dimensions:** 88x148x47mm

**Faceplate Depth:** 7mm

**Fixing Centres:** 120.6mm

**Depth from Mounting Face:** 17.7mm

**Recommended Back Box Depth:** 25mm

**Operating Voltage:** 230v 50Hz

**Maximum Load Rating:** LED; 120W (Max. 10 lamps)

**Maximum Current Rating:** 1.1A

**Terminal (Live) Diameter:** 3.2mm; Capacity: 3 x 1.5mm<sup>2</sup>

**Terminal (Earth) Diameter:** 3.3mm; Capacity: 3 x 1.5mm<sup>2</sup>

**Warranty:** 1 Year



#### Additional Information

**Intended Applications:** Indoor Use Only. Domestic lighting circuits including many dimmable LEDs.

**Safety Advice:** Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers, TRIAC dimmable loads or electric motors. Do not overload. Product Must Be Earthed.

**Applicable Safety Standard:** BS EN 60669-2-1